



Product Specifications

Camera

- 4K dual-lens technology delivers a wide 113° field of view (FOV) with 18X zoom
- 4K 3X varifocal lens: FOV (D/H/V) 92°/81°/50°
- 4K fixed lens: FOV (D/H/V) 113°/105°/71°
- \cdot Sony 4K sensor: ultra-crystal-clear image in any lighting
- Frame rate: (16:9) 1280 x 720 at 60, 30, 15fps; 4K, 3264 x 1836, 2560 x
 1440, 1920 x 1080, 1600 x 900, 960 x 540, 848 x 480, 800 x 448, 640 x
 360 at 30, 15fps; (4:3) 1280 x 960, 800 x 600, 640 x 480 at 30, 15fps
- Adjustable audio fence: Freedom to define wide/ medium/ narrow view fence
 SmartFrame & SmartSpeaker: Automatic tracking and FOV adjustment
- to fit all participants and focus on the speaker
- \cdot Presentation mode: Voice-triggered tracking on both defined areas and speakers
- · Smart gallery* function enhances visibility
- · Gesture control for intuitive camera control
- · WDR, white balance and more image settings via PTZApp 2
- · Minimum focus distance: 100 cm
- People counting API: Enterprises and third-party software providers can obtain people-counting and meeting-interval data tor better understand meeting space usage
- * Requires running PTZApp 2 on a PC

Motorized Pan and Tilt Movement

- \cdot Pan: Total horizontal viewing area 165°
- · Tilt: Total vertical viewing area 101°
- · 10 camera presets

Audio

| · 14-element beamforming microphone array |
|---|
| · 10 meters pickup range* |
| · Volume up to 96 dB SPL at 1/2 m |
| · Echo cancellation |

· Al noise suppression

* The recommended working distance for AI functionality is within 5 meters.

HDMI

| | D 11.1 LIOD 0.4 | (c) | |
|---|------------------|---|----------------|
| One cable solution: | Built-in USB 3.1 | (Gen 1) t | o HDMI adapter |

- · 4K HDMI output to TV*
- * Windows® 7 and MAC OS: Need to install HDMI adapter driver

Connectivity

| • | 12V/5A power adapter |
|---|----------------------|
| | |

- · Mini DIN 6 for RS-232 connection
- \cdot USB 3.1 type B port, backward compatible with USB 2.0
- · HDMI out connection (USB to HDMI adapter)
- · Phone-in (3.5 mm audio Jack)/speaker-out for HA system*
- · RJ45 ports x2: one for Ethernet, one for audio expansion speakerphone/ microphone
- USB 2.0 type A x3: Wireless connection**, USB to support IFP USB touch back, and expansion port

* Need to set up via PTZApp 2 and purchase an audio-out converter from AVer ** Optional wireless dongle needed to connect with mobile phone

Video Format

- · YUV, YUY2, M-JPEG
- \cdot Network video compression formats: H.264
- · Network protocols: RTSP, RTMP

USB

| · 3.1 Gen 1, backward compatible with USB 2.0 | |
|---|--|
| · UVC 1.1 (USB Video), UAC 1.0 (USB Audio) | |

Control

| · IR remote control |
|---|
| WebUI: IP access via Chrome browser (Chrome 76.x or later; Internet Explorer not supported) |
| · VISCA/pelco P/pelco D via RS-232/VISCA over IP |
| · UVC/UAC plug-and-play |
| · PTZApp 2 |
| |

Mount and Security

| · Wall-mount bracket (included) | |
|---------------------------------|--|
| · TV VESA mount kit (optional) | |

· Kensington security lock

System Requirements

Software:

- · Windows® 7/10/11
- · Mac OS X 10.14 or later
- · Chromebox 3 version 94.0.4606.114 or later

Hardware:

- · 3.2 GHz Intel[®] Core[™] i5-4460 processor
- · 4 GB RAM or more
- · USB 3.1 port, backward compatible with USB 2.0

Power Supply

| · AC 100V-240V, 50/60 Hz | |
|--------------------------|--|
| · Consumption: 12V/4.5A | |

Free Applications for Meeting Collaboration (Free Apps support on Windows® and Mac® computers)

EZManager 2: Camera Central Management Software

· Remotely group FW/SW upgrades, control the camera, and manage settings

PTZApp 2: Camera setting software

- \cdot View live video/people-counting/meeting-interval information
- \cdot Smart Gallery/Preset Link
- \cdot Upgrade firmware automatically or manually
- Control the camera
- $\cdot\,$ Set parameters and adjust the camera image
- · Diagnose operating status

EZLive: Broadcasting software

· Enjoy multi-camera, annotating, image capturing, and video recording

Environmental Data

| \cdot Operation temperature: 0 ~ 40°C |
|---|
| · Operation humidity: 20% ~ 80% |
| Storage temperature: -20 ~ 60°C |
| · Storage humidity: 20% ~ 80% |
| |

Package Contents

| · VB350 unit |
|--|
| · Power adapter & cable |
| \cdot USB 3.1 type B to type A cable (3 m) |
| · USB 3.1 type A to type C adapter |
| · QR code card |
| · Wall-mount bracket |
| · Tripod Screws |
| · Remote control |
| · Wall-mount drill paper |

Optional Accessories

| · Mini DIN 6 to RS-232 adapter |
|--|
| · TV VESA mount |
| · 10 m/20 m expansion microphone |
| · 10 m/20 m expansion speakerphone |
| · 5 m USB 2.0 type B to type A cable |
| \cdot Wireless dongle (for connecting with mobile phone) |
| · Audio-out converter (TRS female to TRRS male) |
| |

Dimensions

| Package dimensions: 872 mm | ι (L) x 197 | mm (W) x 260 mi | m (H) |
|--|-------------|-----------------|-------|
|--|-------------|-----------------|-------|

· Package weight: 7.4 kg

- · Camera: 791 mm (L) x 128 mm (W) x 126 mm (H)/3.3 kg
- \cdot Remote control: 150 mm (L) x 42 mm (W) x 19 mm (H)/50 g

Warranty*

· Camera: 3 years

· Accessories: 1 year

*We offer an optional 2-year extended warranty in the European area. Please contact your local agency for details.

Compatible Applications

Zoom, Microsoft® Teams, Skype for Business, Skype, Google Meet[™], Intel® Unite[™], RingCentral, BlueJeans, V-Cube, LiveOn, CyberLink U Meeting[®], TrueConf, Adobe® Connect, Cisco WebEx®, Fuze, GoToMeeting[™], Microsoft® Lync[™], Vidyo, vMix, WebRTC, Wirecast, XSplit, V Cube

 \star For 4K UHD support, please check system/hardware requirements with your software application provider.

^{**} Specifications may vary depending on location and are subject to change without notice.

Product Overview

Front



791 mm (L) x 128 mm (W) x 126 mm (H)

Back



Side



| 1 | Phone-in |
|---|----------------------------------|
| 2 | Audio expansion |
| 3 | RS-232 |
| 4 | USB 2.0 type A (wireless dongle) |



| 1 | DC 12V |
|---|-------------------------------|
| 2 | LAN |
| 3 | USB 3.0 type B (device to PC) |
| 4 | HDMI-out (to TV) |
| 5 | USB 2.0 type A port |