



Poly G7500 System and Accessories

This document covers the following Wi-Fi- and/or Bluetooth- enabled products:

- Poly G7500 System (Models P011)
- Poly G7500 Remote Control (Model P010)

This document also covers the following products that don't contain either Wi-Fi or Bluetooth functionality:

- Poly G7500 System (Models P011 NR)
- Poly® IP Table Microphone (Model P013)
- Poly® IP Ceiling Microphone (Model P014)

Service Agreements

Please contact your Poly Authorized Reseller for information about service agreements applicable to your product.

Safety, Compliance, and Disposal Information

- This equipment is intended for indoor use only.
- This equipment is not intended to be directly connected to outdoor cables.
- Do not spray liquids directly onto the system when cleaning. Always apply the liquid first to a static-free cloth.
- Do not immerse the system in any liquids or place any liquids on it.
- Do not disassemble this system. To reduce the risk of shock and to maintain the warranty on the system, a qualified technician must perform service or repair work.
- There are no user serviceable parts inside this product.
- This equipment is not intended to be operated by children.
- Users must not service any parts in compartments that require a tool to access.
- This equipment should be used only on even surfaces.
- Keep ventilation openings free from any obstructions.
- The ambient operating temperature rating of this equipment is 0-40°C and should not be exceeded.
- In order to remove all power from this unit, disconnect all power cables, including any USB or Power over Ethernet (PoE) cables.
- If the product is powered using PoE, you must use an appropriately rated and approved networking device compliant with IEEE 802.3af, or the power injector identified for use with this product.

Additional Warnings for Products with a Power Supply

- Always disconnect the system from power and telecommunications networks before cleaning or servicing.
- This product is intended to be powered by an external Limited Power Source (LPS) power supply. Use only the type which is supplied with this product.
- This system is considered to be Pluggable Equipment Type A. The socket outlets must be installed near the equipment and be easily accessible.
- Additional Warnings for Products with a Power Cord
- Do not use a power cord that is damaged. This could cause fire or electric shock. Contact the manufacturer for a replacement cord, if necessary.
- Only use a power cord which is appropriately rated and approved relevant to the country of use.
- When connecting to the mains supply, connect only to an earthed supply outlet which is installed near the equipment and is easily accessible.

Additional Warning for Products with Power over Ethernet (PoE) Functionality

- If the product is powered using Power over Ethernet, you must use an appropriately rated and approved networking device, or the power injector identified for use with this product.

WARNING Electrical Safety

Always read product documentation fully before connecting to a power source.

Electrical Specifications

Poly® G7500 System (Model type: P011) 54VDC, 3.3A

Poly® G7500 System (Model type: P011 NR) 54VDC, 3.3A

Poly® G7500 Remote Control (Model type: P010) 3.0VDC AAx2

Poly® IP Table Microphone (Model type: P013) 54VDC, 90mA

Poly® IP Ceiling Microphone (Model type: P014) 54VDC, 90mA External Power Supplies

This product must only be used with an external power supply of the type and specification provided with it. Replacement external power supplies can be obtained from the supplier of your Poly equipment.

PoE Products

Products that are designed to be connected to a Power over Ethernet source must only be connected to a IEEE 802.3af compliant Power over Ethernet (PoE) power source or an IEC60950 limited power source.

The power plug-wall socket combination acts as a disconnection device and must be accessible at all times.

Power Cables

Only use the power cables that are supplied with this product; these are correctly rated for this product.

Installation of the equipment should be carried out by suitably trained people, and must comply with the appropriate local and national electrical codes.

Plug Acts as Disconnect Device

The socket outlet to which this apparatus is connected must be installed near the equipment and must always be readily accessible.

La prise électrique à laquelle l'appareil est branché doit être installée près de l'équipement et doit toujours être facilement accessible.

In addition, all POE sources must meet the Limited Power Source requirements of IEC 60950-1:2005 (2nd Edition); Am1:2009 or IEC 60950-1:2005 (2nd Edition); Am1:2009; Am2:2013; and IEC 62368-1:2014.

En outre, toutes les sources d'entrée doivent obligatoirement répondre aux exigences Source d'alimentation limitée de la CEI 60950-1: 2005 (2e édition); Am1:2009 ou IEC 60950-1: 2005 (2e édition); Am1:2009; AM2:2013; and IEC 62368-1:2014.

Ambient Temperature Guidelines

- Operating temperature: 32 to 104°F (0 to 40°C)
- Storage temperature: -40 to -140°F (-40 to 60°C)
- Remote control temperature: -4 to 140°F (-20 to 60°C)

Installation Instructions

Installation must be performed in accordance with all relevant national wiring rules.

L'Installation doit être exécutée conformément à tous les règlements nationaux applicable au filage électrique.

When using Power over Ethernet (PoE), the equipment is to be connected only to PoE networks, without connections to the outside plant.

Environmental

End of Life Products

Poly encourages you to recycle your end-of-life Poly products in an environmentally considerate way.

We recognize our Extended Producer Responsibility (EPR), in accordance with the requirements of the European Waste Electronic and Electrical Equipment (WEEE) Directive 2012/19/EU.

Battery Replacement, Handling, and Disposal

BT remote control uses two 1.5V AAA batteries. Only use high quality batteries. Insert the batteries according to the markings for plus and minus terminals under the cover at the bottom of the form.

- **Battery Guidance:** Poly takes great care in the selection of its lithium ion and nickel metal hydride batteries and, where used, these have been designed specifically for use in specific Poly products. Only Poly replacement batteries should be used. Replacement batteries can be ordered by your supplier. Detailed instructions on the safe replacement of batteries are provided in the user guide for your product.

Some Poly products are supplied with commonly available alkaline batteries such as AA or AAA types. Where this is the case and replacement is due, they should be replaced as a complete set with new, quality batteries of the correct size and rating. Please observe the polarity of the batteries during installation taking care not to short circuit them. Batteries should be treated and used in accordance with the battery manufacturer's guidance.

- **Toxic Substances:** The batteries supplied by Poly in its products and as replacement parts meet the marking and heavy metal content requirements of the EU Battery Directive. Where batteries include lead, mercury, or cadmium, the levels of these substances are very low and fall below the thresholds that exist in all markets into which they are supplied. Lead acid batteries supplied with certain Poly products carry the Pb symbol indicating presence of lead above the thresholds described above.
- **Battery Disposal:** When a battery has reached the end of its working life, carefully remove it from the product as instructed in the user guide. The battery should be taken to a collection point where it can be recycled or disposed of in an environmentally friendly manner. Do not dispose of the battery in a fire or in unsorted municipal waste.

CAUTION: RISK OF EXPLOSION IF BATTERY IS REPLACED BY AN INCORRECT TYPE. DISPOSE OF USED BATTERY ACCORDING TO THE INSTRUCTIONS.

Please contact typeapproval@hp.com if you have questions or would like additional information.

Restriction of Hazardous Substances Directive (RoHS)

All Poly products comply with the requirements of the EU RoHS Directive. Statements of compliance can be obtained by contacting typeapproval@hp.com.

Waste Electrical and Electronic Equipment (WEEE)



All Poly products that fall within the scope of the EU WEEE Directive carry the crossed wheeled bin symbol, which advises customers not to recycle electronic products in the domestic waste stream but to recycle them safely as e-waste.

Poly Take Back

In addition to any mandated take back requirement, Poly offers free recycling of its branded products to business users. Detailed information is available at <https://www.poly.com/us/en/company/corporate-responsibility/environment>.

Compliance Information by Country

Unless otherwise stated, all compliance statements outlined in this section relate to all products covered by this document.

United States

Caution: Pursuant to 47CFR§15.21 of the FCC Rules, any changes or modifications to this equipment not expressly approved by HP Inc. may cause harmful interference and void the FCC authorization to operate this equipment."

Radiation Exposure Statement

Note: The exposure statement is only applicable to radio device P011.

The antenna used for this transmitter must be installed to provide a separation distance of at least 20 centimeters from all persons and must not be co-located or operating in conjunction with any other antenna or transmitter. This device with its antenna complies with FCC's RF radiation exposure limits set forth for an uncontrolled environment. To maintain compliance, this transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Remote Control (P010) FCC ID: M7N-BW7630

Poly G7500 (P011) FCC ID: M72-P011

Modifications

In accordance with part 15 of the FCC Rules, the user is cautioned that any changes or modifications not expressly approved by Poly Inc. could void the user's authority to operate the equipment.

Class A Digital Device

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

Responsible Party issuing FCC Supplier's Declaration of Conformity:

HP Inc.
1501 Page Mill Road,
Palo Alto 94304

USA

650-857-1501

Modifications - In accordance with part 15 of the FCC rules, the user is cautioned that any changes or modifications not expressly approved by Poly, Inc. could void the user's authority to operate the equipment.

Accessibility

Details of the features offered by this product against the accessibility criteria of Section 508 of the US Disability Act and Section 255 of the US Communications Act can be found at

<https://www.poly.com/us/en/legal/compliance/vpat>.

Australia

Warning: This equipment will be inoperable when mains power fails.

Class A Warning

Warning: This is a class A product. In a domestic environment this product may cause radio interference in which case the user may be required to take adequate measures."

New Zealand

Class A Warning

Warning: This is a class A product. In a domestic environment this product may cause radio interference in which case the user may be required to take adequate measures."

Brazil

Para maiores informações consulte o site da ANATEL - www.anatel.gov.br

Este equipamento não tem direito à proteção contra interferência prejudicial e não pode causar interferência em sistemas devidamente autorizados.

Poly G7500 System

The following table identifies the allowable frequencies of use of Poly G7500 (P011) system in Brazil.

Sistema de videoconferência que opera com as tecnologias Bluetooth e Wi-Fi e implementa os protocolos SIP (UDP e TCP) e H.323.

Faixa Frequência (MHz)	Potência Máxima de Saída (W)	Designação de Emissões	Tecnologia	Tipo de Modulação	Taxa Máxima de Transmissão
2400 – 2483,5	0,0134	954KF7D	Salto em frequência Bluetooth	GFSK	1 Mbit/s
	0,1133	1M30G7D	Salto em frequência Bluetooth	8DPSK	3 Mbit/s
	0,0013	676KF7D	Sequência Direta Bluetooth	GFSK	1 Mbit/s
	0,0012	1M16F7D	Sequência Direta Bluetooth	GFSK	2 Mbit/s
	0,0807	9M08X9D	Sequência Direta 802.11b	DBPSK DQPSK CCK	11 Mbit/s (CCK)
	0,3228	16M6X9D	OFDM 802.11g	BPSK QPSK 16-QAM 64-QAM	54 Mbit/s (64-QAM)
	0,3027	17M8X9D	OFDM 802.11n (20 MHz)	BPSK QPSK 16-QAM 64-QAM	144,4 Mbit/s (64-QAM)
5725 – 5850	0,5260	16M6X9D	OFDM 802.11a	BPSK QPSK 16-QAM 64-QAM	54 Mbit/s (64-QAM)
	0,4624	17M9X9D	OFDM 802.11n (20 MHz)	BPSK QPSK 16-QAM 64-QAM	144 Mbit/s (64-QAM)
	0,4819	36M7X9D	OFDM 802.11n (40 MHz)	BPSK QPSK 16-QAM 64-QAM	300 Mbit/s (64-QAM)
	0,4246	77M0X9D	OFDM 802.11ac (80 MHz)	BPSK QPSK 16-QAM 64-QAM 256-QAM	866,7 Mbit/s (256-QAM)
5470 – 5725	0,3027	-	OFDM 802.11a	BPSK QPSK 16-QAM 64-QAM	54 Mbit/s (64-QAM)
	0,2877	-	OFDM 802.11n (20 MHz)	BPSK QPSK 16-QAM 64-QAM	144 Mbit/s (64-QAM)
	0,2844	-	OFDM 802.11n (40 MHz)	BPSK QPSK 16-QAM 64-QAM	300 Mbit/s (64-QAM)

	0,2032	-	OFDM 802.11ac (80 MHz)	BPSK QPSK 16-QAM 64-QAM 256-QAM	866,7 Mbit/s (256 QAM)
5150 – 5350	0,1161	-	OFDM 802.11a	BPSK QPSK 16-QAM 64-QAM	54 Mbit/s (64-QAM)
	0,1238	-	OFDM 802.11n (20 MHz)	BPSK QPSK 16-QAM 64-QAM	144 Mbit/s (64-QAM)
	0,1858	-	OFDM 802.11n (40 MHz)	BPSK QPSK 16-QAM 64-QAM	300 Mbit/s (64-QAM)
	0,1853	-	OFDM 802.11ac (80 MHz)	BPSK QPSK 16-QAM 64-QAM 256-QAM	866,7 Mbit/s (256 QAM)

O equipamento possui duas antenas internas com ganho de 3dBi.

A medida da potência nas faixas de 5150-5350 MHz e 5470-5725 MHz refere-se à potência média EIRP. O ganho da antena total considerado foi de 6,01 dBi.

Canada

This device is only for indoor use to reduce the potential for harmful interference to co-channel mobile satellite systems

This device contains license-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's license-exempt RSS(s). Operation is subject to the following two conditions:

1. This device may not cause interference.
2. This device must accept any interference, including interference that may cause undesired operation of the device.

Radiation Exposure Statement:

This equipment complies with ISED radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with greater than 20cm between the radiator & your body.

Déclaration d'exposition aux radiations:

Cet équipement est conforme aux limites d'exposition aux rayonnements ISED établies pour un environnement non contrôlé. Cet équipement doit être installé et utilisé à plus de 20 cm entre le radiateur et votre corps.

Industry Canada IC

ICES 003 Nov 2014 ICES Statement

This product meets the applicable Industry Canada technical specifications common to radio and non-radio products.

Le présent matériel est conforme aux spécifications techniques applicables d'Industrie Canada.

This Class A digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de la classe A est conforme à la norme NMB-003 du Canada.

Industry Canada (IC) ID:

Remote Control (P010) IC ID: 7311A-BW7630

Poly G7500 (P011) IC ID: 1849C-P011

This device complies with RSS210 of the Industry Canada rules. Operation is subject to the two following conditions:

- This device does not cause harmful interference.
- This device must accept any interference received, including interference that may cause undesired operation.

Ce dispositif est conforme à la norme CNR-210 d'Industrie Canada applicable aux appareils radio exempts de licence. Son fonctionnement est sujet aux deux conditions suivantes:

le dispositif ne doit pas produire de brouillage préjudiciable, et (2) ce dispositif doit accepter tout brouillage reçu, y compris un brouillage susceptible de provoquer un fonctionnement indésirable.

China

用户须知 欢迎使用惠普 型號:P011 型号: G7500, 型號:P011NR, 型號/型号: P013, 型號/型号: P014 为了您及产品的安全, 请您务必注意如下事项:

1. 产品要和地线相接, 要使用有正确接地插头的电源线, 使用中国国家规定的220V电源。
2. 避免高温和多尘土的地方, 否则易引起产品零部件的损坏。
3. 避免接近高温, 避免接近直接热源, 如太阳光直射, 暖气等其他发热体。
4. 不要有异物或液体落入机内, 以避免零部件短路。
5. 不要将磁体放置于产品附近。

警告

为防止火灾或触电事故, 请不要将该产品淋雨或者放置于潮湿处。

EU

CE Mark

P010 & P011 - Are marked with the CE mark. This mark indicates compliance with Radio Equipment Directive (RED) 2014/53/EU, EU 801/2013 (Networked Standby Regulation), 2011/65 EU RoHS Directive and EC 278/2009 (External Power Supply Regulation).

P011 NR - Is marked with the CE mark. This mark indicates compliance with 2014/35/EU LV Directive, 2014/30/EU EMC Directive, EC 278/2009 External Power Supply Regulation, and 2011/65 EU RoHS Directive.

P012 - Is marked with the CE mark. This mark indicates compliance with 2014/35/EU LV Directive, 2014/30/EU EMC Directive, EC 278/2009 External Power Supply Regulation, and 2011/65 EU RoHS Directive.

P013 & P014 - Are marked with the CE mark. This mark indicates compliance with 2014/35/EU LV Directive, 2014/30/EU EMC Directive and 2011/65 EU RoHS Directive.

Full copies of the Declarations of Conformity can be obtained from HP REG 23010, 08028 Barcelona, Spain

Radio Device Operating Frequency and Power Levels

The following table identifies the allowable frequencies and maximum transmit power.

System: P011

Frequency Range	Maximum Transmit Power EIRP (dBm)
2422 – 2480MHz	18.4dBm
5150 – 5350MHz	23.0dBm
5470 – 5725MHz	22.0dBm
5725 – 5825MHz	21.5dBm

Remote control: P010

Frequency Range	Maximum Transmit Power EIRP (dBm)
2402MHz-2480MHz	-5.26dBm (0.0003W)

India

India RoHS

This product, as well as its related consumables and spares, complies with the reduction in hazardous substances provisions of the “India E-waste (Management and Handling) Rule 2022”. It does not contain lead, mercury, hexavalent chromium, polybrominated biphenyls or polybrominated diphenyl ethers in concentrations exceeding 0.1 weight % and 0.01 weight % for cadmium, except for where allowed pursuant to the exemptions set in Schedule 2 of the Rule.

Japan VCCI

The following VCCI A is for Poly G7500 (models P011 and P011 NR):

P011 is only approved to transmit indoors within the W52 and W53 bands for Japan:

- W52(5180MHz / 5200MHz / 5240MHz)
- W53(5260MHz / 5280MHz / 5320MHz)

VCCI A

この装置は、クラスA機器です。この装置を住宅環境で使用すると電波妨害を引き起こすことがあります。この場合には使用者が適切な対策を講ずるよう要求されることがあります。

VCCI – A

This product can't be connected directly to the telecommunications circuits (or public wireless LANs) of any telecommunications carriers (e.g., mobile communications carriers, fixed communication carriers, or internet providers). To connect this product to the Internet, be sure to connect it via a router.

Power Supply

Caution when using power supply 1456-44342-001 with Poly G7500 products.

製品には、同梱された電源コードをお使い下さい。
同梱された電源コードは、他の製品では使用出来ません。

translation
Please use the attached power cord.
The attached power cord is not allowed to use with other product.

Korea

이 장치는 이동전화, Wi-Fi 또는 블루투스 장치 등 무선통신장치와 매우 근접한 장소에서 사용할 경우 오작동을 일으킬 가능성이 있습니다.

해당 무선설비는 전파혼신 가능성이 있으므로 인명안전과 관련된 서비스는 할 수 없음.

해당 무선설비는 5150~5250GHz 대역에서 실내에서만 사용할 수 있음

Singapore

The following certificate is for Poly G7500 (P011) only:

Complies with
IDA Standards
[DA101619]

South Korea

Product Name	KC Certificate Number
P011	R-R-PLM-P011
P012	R-R-PLM-P012
P013	R-R-PLM-P013
P014	R-R-PLM-P014

Taiwan

The following table identifies the allowable frequencies of use in Taiwan for P011.

工作頻率 (MHz)	頻道數	輸出功率 (dBm)	屬性
2412-2462	11	18.85	WLAN IEEE 802.11b mode
	11	18.91	WLAN IEEE 802.11g mode
	11	18.66	WLAN IEEE 802.11n (HT20) mode
5180-5240	4	20.73	WLAN IEEE 802.11a mode
	4	20.70	WLAN IEEE 802.11n (HT20)/802.11ac (VHT20) mode
	2	20.73	WLAN IEEE 802.11n (HT40)/802.11ac (VHT40) mode
	1	19.72	WLAN IEEE 802.11ac (VHT80) mode
5260-5320	4	20.75	WLAN IEEE 802.11a mode
	4	20.73	WLAN IEEE 802.11n (HT20)/802.11ac (VHT20) mode
	2	20.68	WLAN IEEE 802.11n (HT40)/802.11ac (VHT40) mode
	1	15.60	WLAN IEEE 802.11ac (VHT80) mode
5500-5720	12	20.87	WLAN IEEE 802.11a mode
	12	20.83	WLAN IEEE 802.11n (HT20)/802.11ac (VHT20) mode
	6	20.74	WLAN IEEE 802.11n (HT40)/802.11ac (VHT40) mode
	3	20.61	WLAN IEEE 802.11ac (VHT80) mode
5745-5825	5	20.77	WLAN IEEE 802.11a mode
	5	20.74	WLAN IEEE 802.11n (HT20)/802.11ac (VHT20) mode
	2	20.66	WLAN IEEE 802.11n (HT40)/802.11ac (VHT40) mode
	1	20.59	WLAN IEEE 802.11ac (VHT80) mode

工作頻率 (MHz)	頻道數	輸出功率 (dBm)	屬性
2402-2480	79	12.31	Bluetooth EDR
2402-2480	40	3.25	Bluetooth LE

Class A Statement

警告使用者：

此為甲類資訊技術設備，於居住環境中使用時，可能會造成射頻擾動，在此種情況下，使用者會被要求採取某些適當的對策。

安全警語:

1. “不得打開產品外殼，以免造成安全問題” 或“不要對本設備進行機械或電氣修改，以免造成安全問題”
2. 請勿任意拆裝設備。任何未經授權或認證人員之設備拆裝可能造成嚴重的安全問題。任何問題，請洽您的銷售人員或經銷商尋求協助。
3. 除非安裝手冊或使用手冊中提及，否則請勿嘗試維修您的設備。永遠遵守安裝手冊及使用手冊的說明。

NCC Low Powered Device Statement

取得審驗證明之低功率射頻器材，非經核准，公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。低功率射頻器材之使用不得影響飛航安全及干擾合法通信；經發現有干擾現象時，應立即停用，並改善至無干擾時方得繼續使用。前述合法通信，指依電信管理法規定作業之無線電通信。低功率射頻器材須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

5GHz U-NII Statement

應避免影響附近雷達系統之操作。
高增益指向性天線只得應用於固定式點對點系統。

Taiwanese ROHS

P011:

設備名稱：視訊會議設備，型號（型式）：P011 Equipment name Type designation (Type)						
單元 Unit	限用物質及其化學符號 Restricted substances and its chemical symbols					
	鉛Lead (Pb)	汞Mercury (Hg)	鎘Cadmium (Cd)	六價鉻 Hexavalent chromium (Cr ⁶⁺)	多溴聯苯 Polybrominated biphenyls (PBB)	多溴二苯醚 Polybrominated diphenyl ethers (PBDE)
電路板 (Circuit Board)	—	○	○	○	○	○
外殼 (Shell)	○	○	○	○	○	○
電源線/連接線 (Wire)	○	○	○	○	○	○
電源供應器 (Power Supply)	○	○	○	○	○	○
遙控器 (Remote)	—	○	○	○	○	○
<p>備考1. “超出0.1 wt %”及“超出0.01 wt %”係指限用物質之百分比含量超出百分比含量基準 Note 1: “Exceeding 0.1 wt %” and “exceeding 0.01 wt %” indicate that the percentage content of the restricted substance exceeds the reference percentage value of presence condition.</p> <p>備考2. “◎”係指該項限用物質之百分比含量未超出百分比含量基準值。 Note 2: “◎” indicates that the percentage content of the restricted substance does not exceed the percentage of reference value of presence.</p> <p>備考3. “—”係指該項限用物質為排除項目。 Note 3: The “—” indicates that the restricted substance corresponds to the exemption.</p>						

Get help

For more information about installing, configuring, and administering Poly products or services, go to [Poly Support](#).

Related Poly and partner resources

See the following sites for information related to this product.

- [Poly Support](#) is the entry point to online product, service, and solution support information. Find product-specific information such as Knowledge Base articles, Support Videos, Guide & Manuals, and Software Releases on the Products page, download software for desktop and mobile platforms from Downloads & Apps, and access additional services.
- The [Poly Documentation Library](#) provides support documentation for active products, services, and solutions. The documentation displays in responsive HTML5 format so that you can easily access and view installation, configuration, or administration content from any online device.
- The [Poly Community](#) provides access to the latest developer and support information. Create an account to access Poly support personnel and participate in developer and support forums. You can find the latest information on hardware, software, and partner solutions topics, share ideas, and solve problems with your colleagues.
- The [Poly Partner Network](#) is a program where resellers, distributors, solutions providers, and unified communications providers deliver high-value business solutions that meet critical customer needs, making it easy for you to communicate face-to-face using the applications and devices you use every day.
- [Poly Services](#) help your business succeed and get the most out of your investment through the benefits of collaboration. Enhance collaboration for your employees by accessing Poly service solutions, including Support Services, Managed Services, Professional Services, and Training Services.
- With [Poly+](#) you get exclusive premium features, insights and management tools necessary to keep employee devices up, running, and ready for action.
- [Poly Lens](#) enables better collaboration for every user in every workspace. It's designed to spotlight the health and efficiency of your spaces and devices by providing actionable insights and simplifying device management.

Privacy policy

Poly products and services process customer data in a manner consistent with the [Poly Privacy Policy](#). Send comments or questions to privacy@poly.com.

Copyright and trademark information

© 2023 Poly. All trademarks are the property of their respective owners.

HP Inc.
1501 Page Mill Road,
Palo Alto 94304
USA

650-857-1501